

## AT-T8 Series

### LED T8 Retrofit Tube Lamp



#### Approvals

DLC, UL, Lighting Facts, ROHS

#### Power Consumption

10w (2ft), 18w (4ft), 40w (8ft)

#### Input Voltage

120-277

#### Dimming Options

Not dimmable

#### Lumen Output

1050/1950, 4350 lm

**Desc:** LED T8 Retrofit Lamp

#### Details

AT-T8 LED lamps are suitable for replacement of existing T8 or T12 linear fluorescent lamps. Emits high CRI light with no flicker. Existing ballast must be bypassed by a qualified professional. Available in multiple color temperatures to match existing lighting. Cast aluminum body acts as integrated heat sink for excellent thermal management. UL and DLC listed, 3 year warranty.

#### Features

Energy efficient: save up to 70% in energy costs  
High lumen output  
Mercury free  
Instant-on at 100%

#### Warranty

3 years- rated lifespan 50,000 hours

#### Applications

Retail and commercial, education, government, industrial

#### Ordering Information

**Sample #:** AT-T8-4FT18W-40

Series	Style/Size	Color Temp		
AT-T8	2FT10W- 2 foot	30- 3000K		
	4FT18W- 4 foot	40- 4000K		
	8FT40W- 8 foot	50- 5000K		

Caution: Risk of electric shock. Do not open. No user serviceable parts inside. Turn off power before inspection, installation or removal. Ensure that all batteries and capacitors have been discharged.

<http://www accuratetechinc.com>

**AT-T8  
Data Sheet**



**PHYSICAL DATA**

	DIMENSIONS					
	BASE	FINISH	DIAMETER (IN)	LENGTH (IN)	WIDTH (IN)	HEIGHT (IN)
2Ft	G24/ 1 PIN	W, S	1	24		
4Ft	G24/ 1 PIN	W,S	1	48		
8Ft	G24/ 1 PIN	W,S	1	96		

**ELECTRICAL DATA**

	POWER (W)	MAX. INPUT (V)	CONTROL	POWER FACTOR
2Ft	10	100-277	S	
4Ft	18	100-277	S	
8Ft	40	100-277	S	

**LIGHTING DATA**

	FLUX (LM)	EFFICACY (LM/W)	BEAM ANGLE	CRI	EQUIVALENT
2Ft	1050-1100	105	200	>83	17W T8
4Ft	1950-2000	105	200	>83	32W T8
8Ft	4350-4400	105	200	>83	60W T8

**SAFETY & LEGAL DATA**

	WEATHER RATING	UL	DLC	ENERGY STAR	WARRANTY (YRS)
2Ft	DRY LOC.	X	X		3
4Ft	DRY LOC.	X	X		3
8Ft	DRY LOC.	X			3

Caution: Risk of electric shock. Do not open. No user serviceable parts inside.  
Turn off power before inspection, installation or removal. Ensure that all batteries and capacitors have been discharged.

<http://www.accuratetechinc.com>